

Light dependent resistors

Two cadmium sulphide (cdS) photoconductive cells with spectral responses similar to that of the human eye. The cell resistance falls with increasing light intensity. Applications include smoke detection, automatic lighting control, batch counting and burglar alarm systems.

Guide to source illuminations

Light source	Illumination (Lux)
Moonlight	0.1
60W bulb at 1m	50
1WMES bulb at 0.1m	100
Fluorescent lighting	500
Bright sunlight	30,000



Light memory characteristics

Light dependent resistors have a particular property in that they remember the lighting conditions in which they have been stored. This memory effect can be minimised by storing the LDRs in light prior to use. Light storage reduces equilibrium time to reach steady resistance values.

NORP12 (**RS** stock no. 651-507)

Absolute maximum ratings

0	
Voltage, ac or dc peak	320V
Current	75mA
Power dissipation at 30°C	250mW
Operating temperature range	60°C to +75°C

NORP12 **RS** stock number 651-507 NSL19-M51 **RS** stock number 596-141

Electrical characteristics

 $T_A = 25^{\circ}C. 2854^{\circ}K$ tungsten light source

Parameter	Conditions	Min.	Тур.	Max.	Units
Cell resistance	1000 lux	-	400	-	Ω
	10 lux	-	9	-	kΩ
Dark resistance	-	1.0	-	-	$\mathbb{M}\Omega$
Dark capacitance	-	-	3.5	-	pF
Rise time 1	1000 lux	-	2.8	-	ms
	10 lux	-	18	-	ms
Fall time 2	1000 lux	-	48	-	ms
	10 lux	-	120	-	ms

1. Dark to 110% R_L

2. To 10 imes R_L

 R_L = photocell resistance under given illumination.

Features

- Wide spectral response
- Low cost
- Wide ambient temperature range.









*1Ftc=10.764 lumens

Absolute maximum ratings

Voltage, ac or dc peak	100V
Current	5mA
Power dissipation at 25°C	50mW*
Operating temperature range	25°C +75°C

*Derate linearly from 50mW at 25°C to 0W at 75°C.

Electrical characteristics

Parameter	Conditions	Min.	Тур.	Max.	Units
Cell resistance	10 lux 100 lux	20 -	- 5	100 -	$k\Omega \ k\Omega$
Dark resistance	10 lux after 10 sec	20	-	-	MΩ
Spectral response	-	-	550	-	nm
Rise time	10ftc	-	45	-	ms
Fall time	10ftc	-	55	-	ms







232-3816

Typical application circuits









(Relay energised when light exceeds preset level.) Incorporates a balancing bridge and op-amp. R_1 and NORP12 may be interchanged for the reverse function.

The information provided in **RS** technical literature is believed to be accurate and reliable; however, RS Components assumes no responsibility for inaccuracies or omissions, or for the use of this information, and all use of such information shall be entirely at the user's own risk. No responsibility is assumed by RS Components for any infringements of patents or other rights of third parties which may result from its use. Specifications shown in RS Components technical literature are subject to change without notice.